

800MX (440KV/4530) MOTOR USERMANUAL 馬達說明書 ALIGN

800MX MOTOR 關於800MX馬達



Power and torque requirements of enthusiasts, the high output 800MX motor was born in Align's R&D lab. With dramatic increase in torque and power output, capable of 4440 watts continuous power output and 8800 watts of burst power! 800MX Motor has passed various thorough inspections made by our technical department, including motive testing, static testing, magnetic field testing, heat resistance and magnetic loss testing, running balance and vibration testing, noise testing, and many hours of actual loading and flying testing, etc. Align is proud to provide the latest innovations in RC Modeling to its consumers. Please enjoy your Align products safely.

亞拓特別針對玩家大動力、高扭力的需求，研發設計出為爆發動力而生的800MX馬達，動力輸出與扭力表現大幅提升，持續輸出功率達4440W，瞬間最大輸出功率可達8800W。

本公司生產的高扭力高轉速800MX馬達，適用於RC電動商品，其高功率高效率輸出特性，適合電動飛機/電動直升機之高扭力高轉速驅動動力用途。速度控制可採本公司城市售規格刷電子變速器。轉子採用高強性材料鍍鍍錳精製而成，定子採用本廠NC自動繞線與高強度樹脂成型保護，耐高溫低震動。心軸採用高硬度高質性特種鋼及雙ZZ高速精密軸承設計，且經由亞拓獨立開發設計技術，使用壽命長、效率高、耐撞不易變形、低震動、高效率800型無刷馬達。該項新產品已通過本廠技術單位，實施精密嚴格動、靜態、磁場特性、強磁耐高溫測試、通過平衡震動及噪音、負載實際飛行動態性能等全項嚴格檢測。

SPECIFICATION 尺寸規格




ILLUSTRATION 接線示意圖



The motor rotates in different direction with different brand ESCs. If the wrong rotating direction happens, please switch any two cables to make the motor rotates in right direction.

由於各品牌電子變速器的馬達旋轉方向不盡相同，若發生轉向錯誤時，請將馬達與電子變速器的接線在兩極對調即可。

KV KV值	440K(RPM/V)	Input voltage 輸入電壓	12S
Stator Diameter 定子外徑	45 mm	Stator Thickness 定子高度	30mm
Stator Arms 矽鋼片槽數	12	Magnet Poles 磁鐵極數	10
Max continuous current 最大持續電流	100A	Max instantaneous current 最大瞬間電流	200A(2sec/2秒)
Max continuous power 最大持續功率	4440W	Max instantaneous power 最大瞬間功率	8800W(2sec/2秒)
Dimension 尺寸	Shaft 軸 ϕ 6x56.7x94.5mm	Weight 重量	Approx.約 508g

FEATURES 特性說明

1. 800MX features high efficiency, superior power, excellent torque, low current draw and low temperature; it's capable of maintaining consistent torque and head speed through continuous F3C maneuvers.
2. Due to the 800MX's high efficiency and low current draw, the standard equipment 120A electronic speed controller are sufficient to experience the power of this motor, and extend battery longevity.
3. The 800MX motor armature had a special balance adjust to improve the serious shaking problem.
4. Maintenance free, high torque, high efficiency, stable and quiet.
5. High-speed ball bearings, powerful magnetic outrunner rotor.
6. Suitable for T-REX 700E、T-REX800E F3C helicopters.

1. 800MX馬達有著高效率、大動力、高扭力、低耗電流與低溫度的表現，F3C大角度的動作可以感受雙扭力輸出，整架飛行都能維持一致的動力輸出，主旋翼幾乎是維持在固定轉速，不掉轉。
2. 800MX馬達的高效率、低電流表現，電子變速器只需要原廠120A的標準配備，就能完全展現馬達的威力，與延長電池的使用壽命。
3. 800MX馬達轉子皆經過特殊平衡校正，改善一般無外殼轉馬達平衡不佳，易產生嚴重震動的缺失。
4. 免保養、高扭力、高效率、低噪音、低溫昇、控制穩定。
5. 高速滾珠軸承、高磁通轉子。
6. 適用T-REX 700E/800E F3C。