

Auto Battery

Identification

PATENTED TECHNOLOGY

Integrated LiPo Balance **Charging Wires**



MAXX © Cable High-Efficiency 12-Gauge Silicone Jacketed Wire

Traxxas® iD™ chargers auto-detect iD equipped Traxxas batteries and automatically optimize charge settings for worry-free charging*

Use with Traxxas iD Chargers for the easiest and safest charging solution

45934 4S - 14.8 Volts 25C Sustained 50C Burst **3C** Charge Traxxas Certified to meet the power and top speed requirements of Traxxas models

Dimensions (mm): 17844x50.5 Max Charge Rate: 3C (20.1A) Charge Rate: 1C (6.7A) 81.69 :show the Watt Hours: Max Burst Rate: 50C (336A) Continuous Discharge: 25C (168A) Configuration: 4s1p Specifications:

Weight: 22.7oz (644g)

Balance Wires

The balance wires are integrated into the Integrated Balance Connector

and tiny connectors are eliminated. Fragile balance wires, balance boards, connection to Traxxas Lipo chargers. main connector for fast, easy, and rugged

Traxxas Exclusive!

A Traxxas LiPo charger or adapter compatible with the integrated balance connector is required for charging this battery.

WARNING! CAUTION! DANGER!

FIRE HAZARIDI Read and follow manufacturer's charging and handling instructions, warnings and precautions instructions. Never allow children under 14 years old to charge batteries without the supervision of a responsible, knowledgeable adult.

• If any battery or cell is damaged in any way, do NOT charge,

• ALWAYS confirm charger settings match this battery prior proof container and on a non-flammable surface such as concrete. discharge, or use the battery.

 Do NOT disassemble, crush, short circuit or expose to flame. Do NOT exceed the maximum recommended charge rate.

NEVER leave batteries unattended during charging.

 \bullet $\ensuremath{\mathsf{REMOVE}}$ flammable items and combustible materials from the

While charging, always place the battery in a fire retardant/fire

• DO NOT charge with a NiMh only charger. Use ONLY a Traxxas iD equipped LiPo charger with this battery.

ALWAYS charge batteries in a well-ventilated area.

charging area.

If you have any questions, call TRAXXAS Customer Support at 1-888-TRAXXAS (1-888-872-9927) Outside the US +1-972-549-3000

4=CELL LIPO





0

 $oldsymbol{\Phi}$